



**Article no.: 843338**

KAPEGO SC-104 Switch Converter, DC 15-36V, 4 Channel, black



**Technical Data**

<b>POWER SUPPLY</b>	DC 15-36V
<b>POWER CONSUMPTION</b>	max. 1.2W
<b>STANDBY LOSS</b>	0.5W
<b>OUTPUT VOLTAGE</b>	DC 0-10V (max. 4x 15mA)
<b>CONTROLABLE CHANNELS</b>	4

**Dimensions & Weight**

<b>LENGTH</b>	115 mm
<b>WIDTH</b>	57 mm
<b>HEIGHT</b>	25 mm
<b>PRODUCT WEIGHT</b>	0.11 kg

**Features:**

The SC-104 is the tool you need to convert a simple push switch or rocker switch into an intelligent 1-10V dimmer that can control and dim any power supply, PWM converter or ballast with an 1-10V input.

- It can be operated with any push switch or rocker switch
- Only 2 wires from the switch to the controller are needed
- Easy to install into existing installations
- 4 individual input connections linked with 4x 1-10V outputs (OFF=0-1V)
- Very smooth up and down dimming, by press & hold function
- Soft light ON & OFF function
- Memory for last light setting (freeze function for power failure)
- Strong ABS-PC housing with attachable DIN Rail adapter



**Deko-Light**

**kapego**

